

Relay Module

S312N

Transistor driven DPCO Interface relay modules. The device accepts a variety of input conditions (Voltage, Logic, Closed Circuit and Open Circuit) for interfacing various signals via voltage free DPCO contacts.

Specification	S312N
Led Current	N/A
Switch Contacts	DPCO contacts rated at 2A
Visual Indication	1 x Red
Integral Sounder Level	N/A
Supply Voltage	12vdc
Supply Input Current	40 mA max per relay
Tamper	No
Material	PCB Module with self-adhesive backing
Dimensions	57 x 47 x 14 mm
Weight	0.024kg
IP Rating	N/A
Approvals	UKCA and CE marked, ROHS compliant

Benefits and Features

- Self adhesive backed for easy mounting
- NPN version
- S312N available in 20 off packs
- 12vdc powered
- Transistor driven interface relay
- Screw terminals for easy connection
- Manufactured in the UK

